

Take Conferencing Audio to New Heights

## AVer FONE700

Ceiling Speakerphone System for Rooms of Any Size



### Product Specifications

#### FONE700 System (Hub + Speakerphone)

- Full duplex acoustic system for optimal meeting experience
- One cable daisy chain up to 4 speakerphones for flexible installation
- Versatile connectivity for video conferencing integration
- Advanced acoustic features optimized for ceiling installation, powered by AVer algorithm for uncompromised audio quality across daisy-chain setup
  - Acoustic echo cancellation (AEC)
  - Advanced noise reduction (NR)
  - Automatic gain control (AGC)
  - Double-talk detection
  - De-reverberation
  - AI noise suppression
  - Voice fencing
- Audio tracking enabled with AVer USB camera

#### FONE700 Speakerphone

- 3 units directional + 18 units omnidirectional microphones
- Acoustic pickup angle: 360 degrees per unit
- Acoustic pickup range\*: up to 3.5 m radius per unit
- Speakerphone volume: adjustable, up to 99 dB SPL at 0.5 m
- Daisy chain: up to 4 speakerphones with AVer-supplied RJ45 cable(s)
- Audio-tracking range\*: up to 2.5 m radius for optimal experience

*\*Optimal performance varies depending on acoustic treatment of meeting room*

#### FONE700 Hub

- Acoustic DSP Hub for speakerphone, expandable up to 3 additional units
- One cable 48 V powered from Hub to 4 speakerphones via AVer-supplied Cat5 cable; no additional power required
- Integration for video conferencing with versatile connections for\*:
  - USB 3.0 type-C port for PC connection
  - USB 3.0 type-A ports for AVer USB cameras hub; up to 2 cameras connected
  - USB 2.0 type-A port for BT dongle connection
  - Speakerphone port for AVer proprietary daisy-chained technology
  - LAN port for remote control and AVer Virtual Audio technology
  - 4K HDMI output (for USB to display output from connected PC)
  - 3.5 mm line-out jack for external speaker or hearing aid system
  - 3.5 mm phone-in jack for phone calls or external microphone input

*\*Settings configured in PTZApp 2 or via web browser*

#### Connection

- USB with USB Audio Class (UAC) 1.0
- RJ45 with AVer proprietary Virtual Audio (IP streaming)

#### Control

- USB Plug and Play: Video conference software with mute/unmute, volume up/down
- PTZApp 2 for advanced settings and AVer Virtual Audio streaming
- Web browser for advanced remote settings

## Security

---

- Safety tether attachment points on speakerphone
- Kensington slot on Hub

## Power Supply

---

- AC 100V to 240V, 50/60 Hz
- Consumption: 48V, 3.75A

## PTZApp 2: Value-added AVer Free Software for Meeting Collaboration

---

- Auto/manual firmware upgrades
- Acoustic settings
- Operating status diagnosis
- AVer proprietary Virtual Audio streaming technology

## System Requirements for PTZApp 2

---

- Operating system:
  - Windows® 7/10/11 or later
  - Mac OS X v10.14 or later
- Processor: 3.2 GHz Intel® Core™ i5-4460 or later
- Memory: 4 GB RAM

## Environmental Data

---

- Operating temperature: 0°C to 40°C
- Operating humidity: 20% to 80%
- Storage temperature: -20°C to 60°C
- Storage humidity: 20% to 80%

## Dimensions

---

- Package dimensions: 39.2 x 39.2 x 24 cm
- Package weight: 7.83 kg
- Hub: 21 x 12.5 x 4 cm/1.06 kg
- Speakerphone: 37 x 37 x 16.5 cm/3.31 kg

## Package Contents

---

- FONE700 Ceiling Speakerphone
- FONE700 Hub
- Power adapter (48V/3.75A)
- Power cable
- RJ45 cable (10m)
- USB-C 2.0 cable (5m)
- Hub wall mount bracket with screws
- Mount drill template
- Quick Start Guide

## Optional Accessories

---

- Ceiling Speakerphone with 10m cable supplied (for daisy chain)
- RJ45 cable (10/20m)
- Ceiling mount kit
- BT dongle

## Warranty

---

- Speakerphone/ hub: 3 years
- Accessories: 1 year

*\*We offer an optional 2-year extended warranty in the European area. Please contact your local agency for details.*

## Compatible Applications

---

Software supports UAC connections, e.g., Zoom, Zoom Rooms, Microsoft Teams, Microsoft Teams Rooms, Google Meet, etc


*\*Specifications may vary depending on location and are subject to change without notice.*

Speakerphone



- |                 |                         |                       |
|-----------------|-------------------------|-----------------------|
| 1 Speakerphone  | 3 RJ45 out port (red)   | 5 Tie-off point       |
| 2 LED indicator | 4 RJ45 in port (yellow) | 6 M4 screw holes (x4) |
|                 |                         | 7 1/4"-20 screw hole  |


Hub



- |                          |                                  |                                     |                                      |
|--------------------------|----------------------------------|-------------------------------------|--------------------------------------|
| 1 Power/Bluetooth button | 5 Status LED indicator           | 7 Kensington lock                   | 12 USB 3.0 type-C port               |
| 2 IR receiver port       | 6 Bluetooth status LED indicator | 8 LAN port                          | 13 USB 3.0 type-A port (for cameras) |
| 3 Bluetooth dongle port  |                                  | 9 USB 3.0 type-A port (for cameras) | 14 RJ45 speakerphone port (red)      |
| 4 HDMI-out port          |                                  | 10 3.5 mm phone-in jack             | 15 DC power jack (48V)               |
|                          |                                  | 11 3.5 mm audio-out jack            |                                      |

Mounting Options

Ceiling mount



Suspension mount



VESA mount

